

Operation of Radium LED Star Long 2G11

Compatibility list: tested gear for use with ECG.

Radium

compatible

incompatible

RL-LONG 36

43218816

Manufacturer	Model	Reference no.	Number of Lamps**
Helvar	EL1X39/36ngn5	2050000258251	1
Helvar	EL 2X39/36 ngn5	8595209930170	2
OSRAM	Qti 1x14/24/21/39 GII	4008321383334	1
OSRAM	Qti 2x14/24/21/39 GII	4008321383396	2
OSRAM	QT 1X36 DIM	4008321645623	1
OSRAM	QTP-OPTIMAL 1X18-40	4008321873743	1
OSRAM	QTP-OPTIMAL 2X18-40	4008321873767	2
OSRAM	QTP-DL 1X36-40	4008321117908	1
OSRAM	QTP-DL 2X36-40	4008321117922	2
Philips	HF-B 136/236 TLD EII 220-240	9137 001 928	1
Philips	HF-B 136/236 TLD EII 220-240	9137 001 928	2
Philips	HF-B 136 TLD EII 220-240	9137 001 926	1
Philips	HF-P 118/136 TL-D II		1
Philips	HF-P 218/236 TL-D III	91166400	2
Philips	HF-S 118/136 TL-D II	9137130321	1
Philips	HF-S 336 TL-D II	9137 130 327	3
Philips	HF-Pi 1 14/21/24/39 TL5 EII	9137 006 240	1
Philips	HF-Pi 2 14/21/24/39 TL5 EII	9137 006 242	2
Philips	HF-R TD 236 PL-L EII		2
Philips	HF-R 236 PLL EII 220-240	9137 006 200	2
Tridonic	PC 1/14-35/24/39 T5 PRO-M Ip	22176182	1
Tridonic	PC 1/36 TCL PRO	87500507	1
Tridonic	PC 2/36 TCL PRO	87500518	2
Tridonic	PC 1X36 T8 TEC	87500258	1
Tridonic	PC 2X36 T8 TEC	87500259	2
Tridonic	PC 2X36 T8 TEC	87500116	2
Tridonic	PC 2X36/4X18 T8 TEC	87500260	2
Vossloh	ELXc 140.862	188140	1
Vossloh	ELXC 240.863	188616	2
Vossloh	ELXC 236.208	188705	2

** tested and proven working at ECG regarded, luminous flux may deviate.

The compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment, and the results can vary in certain field applications due to a number of factors.

Radium does not take over any responsibility, warranty or liability that this results can also achieved by using the devices under other conditions, or when using successor models of the tested devices, or different models of the same manufacturer, or when using other LED tube types.

The absence of a ballast from this chart does not necessarily imply incompatibility.

When installing, please, refer to and observe the ballast manufacturer's instructions for installation.

LED tubes contain several electronic components. Under unfavourable conditions these can lead to acoustic noise. In case of resonance even low noise can cause audible effect. Possible factors influencing this are the installation, the design of the tube holder and the luminaire (acoustic resonance effect) as well as the ballast (harmonic or electronic resonance).

Validity: These compatibility lists are updated in irregular intervals. The user is responsible to ensure that the information they have is up to date and still valid. Once a new compatibility list has been issued, former editions are to be seen as invalid and disposed of.

Errors and omission excepted.

Please note version, current and more lists on www.radium.de/compatibility