

Operation of Radium LED Star Tubes HF/UN

Compatibility list: tested gear for use with ECG.



Luminous flux may deviate more than 10% off specification.
non compatible

RL-T5 HO 54

43519549

Manufacturer	Model	Number of Lamps**
BAG	BCS49.1FX-11	1
BAG	MLS80.1FR-11/220-240	1
BAG	MLS80.1/54.2FR-11/220-240	1
BAG	MLS80.1/54.2FR-11/220-240	2
OSRAM	QT FIT 5/8 1x54-58	1
OSRAM	QT FIT 5/8 2x54-58	2
OSRAM	QT-FQ 1x54/230-240	1
OSRAM	QTi 1x28/54/35/49 GII	1
OSRAM	QTi 2x28/54/35/49 GII	2
OSRAM	QTi DALI 1x28/54 DIM	* without dim (not guaranteed)
OSRAM	QTi DALI 2x28/54 DIM	* without dim (not guaranteed)
OSRAM	QTP-OPTIMAL 1X54-58	1
OSRAM	QTP-OPTIMAL 2X 54-58	2 *
Philips	HF-P 1 54/1 55 TL5 HO/PL-L III IDC	1
Philips	HF-P 2 54/2 55 TL5 HO/PL-L III IDC	2
Philips	HF-Pi 1 28/35/49/80 TL5 EII 220-240	1
Philips	HF-Pi 2 28/35/49/80 TL5 EII 220-240	2
Philips	HF-S 1 54 TL5 II	1
Philips	HF-S 2 54 TL5 II	2
Tridonic	PC 1x54 T5 TOP Ip	1
Tridonic	PC 2x54 T5 TOP Ip	2
Tridonic	PC 1x54 T5 PRO Ip	1
Tridonic	PC 2x54 T5 PRO Ip	2

** tested and proven working at ECG regarded, luminous flux may deviate.

The compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment, and the results can vary in certain field applications due to a number of factors. Radium does not take over any responsibility, warranty or liability that this results can also achieved by using the devices under other conditions, or when using successor models of the tested devices, or different models of the same manufacturer. In case of non-observance of the instructions, safety risks like overheating of RaLED Tube(s) or ECG may occur in rare cases. This lamp is designed for general lighting service (excluding for example explosive atmospheres). Since only the lamp is replaced there is no constructive modification to the luminaire. This lamp may not be suitable for use in all applications where a traditional fluorescent lamp has been used. The temperature range of this lamp is more restricted. In cases of doubt regarding the suitability of the application the manufacturer of this lamp should be consulted. This product includes one LED Tube and one instruction manual.